

OPTOTRONIC - 4DIM LT2 IP20

DALI, AstroDIM, StepDIM, MainsDIM – constant current LED drivers



Áreas de aplicação

- Iluminação viária e urbana
- Indústria
- Indicado para aplicações de exterior em luminárias com IP > 54
- Indicado para uso em luminárias de exterior com classe de proteção I e II

Benefícios do produto

- Funcionalidade 4DIM num dispositivo (StepDIM, AstroDIM, MainsDIM, DALI)
- Elevada proteção contra choque: até 10 kV (1 pulso) / 8 kV, na classe de proteção I ou II
- Baixa tolerância de rendimento luminoso através da baixa tolerância da corrente de saída de $\pm 3\%$
- Grande flexibilidade devido à ampla temperatura de funcionamento de $-40 \dots 55^\circ\text{C}$ ou 60°C
- Proteção através do duplo isolamento entre a entrada de corrente e saída LED

Características do produto

- Disponível em diferentes potências: 40 W, 60 W, 90 W, 165 W
- Tensão de entrada: 120...277 V (40 W), 170...240 V (60 W, 90 W, 165 W)
- Faixa de saída de corrente: 70...1.050 mA
- Flexibilidade de definição de corrente com um cabo adicional (LEDset2)
- Permite economia de energia nas fases de crepúsculo
- Função DIM de tensão de rede para regulação através de corte de fase
- Interface isolado DALI para sistemas de telegestão bidirecional
- Consumo de energia em stand-by: < 0,5 W
- Proteção contra sobreaquecimento através de NTC externo

Ficha técnica da família de produto

Equipamento / Acessórios

- É necessário o hardware DALI magic para configuração de 4DIM ECGs
- Programável através de software Tuner4TRONIC

Informações sobre aplicações

Para obter mais informações sobre aplicações e gráficos acesse a ficha técnica do produto.

Texto ficha técnica

- Default output current is 700 mA without any resistor connected to the LEDset port. As soon as the driver detects one time a resistor value within the resistor range of 2.37 kOhm (1050 mA) and 24.9 kOhm (200 mA) for more than 3 s, the driver activates the LEDset2 mode.
- The driver withstands an input voltage of up to 350 Vac for a maximum of two hours. Shut down of output load might occur in case the supply voltage exceeds the declared input voltage range.
- Shut down of output load happens if the input voltage of the load is below the allowed minimum output voltage of the driver. The driver automatically tries to switch on the load cyclically.
- In case the input voltage of the load exceeds the output voltage range of the driver, it automatically reduces the output current to keep the output voltage controlled to the maximum allowed output voltage.
- The driver automatically reduces the output current in case the maximum allowed output power is exceeded.
- The driver automatically adjusts the output voltage to the maximum output voltage if no load is connected and switches off the load after some seconds. Hot-plug of the load or external switching on the secondary side is not allowed.
- The driver is protected against temporary overheating by automatic reduction of the output current down to 30 % and then switches off.
- The EQUI pin shall be connected to the heat sink of the LED module to improve the surge withstand capability of the system and EMI in critical luminaires.
- Several external NTCs are supported for temperature protection of the LED module or luminaire. The type of NTC can be selected in the programming software in the temperature based mode. By default the resistor based mode is activated with following values: start derating: 6.3 kOhm, end derating 5.0 kOhm, shut off: 4.3 kOhm, derating level 50 %.
- The default dimming mode is StepDIM / AstroDIM / DALI (wiring selection) with following values for:- StepDIM: 100 % on, 50 % dimming level if SD port is active, fade time 180 s- AstroDIM: 100 % on, 50 % dimming level, 6 h dimming duration, start of dimming duration 2 h before the middle of the average switched-on time, fade time 180 s
- The constant lumen feature is disabled by default.
- For MainsDIM dimming mode and for 170 Vac input voltage condition the output power should not exceed 85 % of the maximum declared output power.
- For input voltage of 170...190 Vac, the maximum allowed output power is linear limited starting from 100 % at 190 Vac down to 85 % at 170 Vac, except for the 40 W type.
- If any output level is below the physical min level, the physical min level will be used.
- In case the 3DIM and 4DIMLT2 devices are operated on one common control phase connected to SD input the 3DIM devices need to have a relay as described in the 3DIM application guide.
- The SD port is suitable for three phase systems with 220...240 Vac, for other input voltages only single phase systems are supported.
- For further details please consult the 4DIMLT2 application guide.

Vendas e suporte técnico

Vendas e suporte técnico www.osram.br

Ecodesign regulation information:

Intended for use with LED modules.

The forward voltage of the LED light source shall be within the defined operating window of the control gear in all operating conditions including dimming if applicable.

Separate control gear and light sources must be disposed of at certified disposal companies in accordance with Directive 2012/19/EU (WEEE) in the EU and with Waste Electrical and Electronic Equipment (WEEE) Regulations 2013 in the UK. For this purpose, collection points for recycling centres and take-back systems (CRSO) are available from retailers or private disposal companies, which accept separate control gear and light sources free of charge. In this way, raw materials are conserved and materials are recycled.

Retrato

Sujeito a alteração sem prévio aviso. Sempre utilize a versão mais recente.